Hybrid ANC Wireless Headphones

LIVEY 950BT

※LIVEY

User Manual

List of annexes



Technical Parameters

Model No.: LIVEY 950BT
Speaker Sensitivity: 110 ±3dB at 1kHz
Impedance: 36Ω ±15%
Frequency Range: 20Hz~ 20kHZ
Microphone Sensitivity: -38 ±1dB
ANC Version: V5.4
Battery Capacity: 1000mAh
BT distance:10 meters
Playback time(ANC OFF): about 100 hours
Playback time (ANC ON): about 60 hours
Charging time: Approx. 3 hours
Charging port: USB Type-C
Input voltage: DC 5V ⎓ 1A
Ear-Cushion Height Depth: Maximum ≈38dB
Dimensions(L*W*H): 197*188*79 mm
Total weight: about 290g

Botton Function



① Multi-function MFB buttons/on/off/play/pause/answer/hang up/volume up/volume down/previous song/next song/clear pairing
② ANC key/ANC mode switching/Voice assistant on/ Voice assistant off/ Last call replay/ Teams answer and hang up
③ Reminder light
④ Type-C charging port
⑤ 3.2mm audio jack
⑥ Microphone

Quick Guide



① Multi-function button=Power on/off
② Flip up to mute/ Flip down to speak
③ Rotate it for clearer voice
④ Long press multi-function button+ANC key for 1 second to connect another mode(BT/Dongle)
⑤ ANC key
⑥ Hidden dongle for low latency

Multi-function MFB button	
Power on	Press and hold for 2 seconds
Power off	Press and hold for 5 seconds
Play/Pause/Answer/Hang up	Click one time
Reject call	When a call comes in, Press and hold for 2 seconds
Previous song	Triple Strike
Next song	double click
Volume Up	Rotate clockwise
Volume Down	Counterclockwise rotation
Eliminate pairing	In the shutdown state, Press and hold for 8 seconds
Connect to another mode(BT/Dongle)	Quickly tap the button 5 times

ANC button	
Switch ANC mode	Click
Quick mute	double click (During Live Call)
Activate/deactivate voice assistant	Triple Strike
Answer/end call in Teams(2.4G Mode)	Long press for 1 second

Microphone	
Microphone on	Open the microphone
Microphone Mute	Closed microphone lever

+ MFB+ANC button	
Connect to another mode(BT/Dongle)	Long press both buttons for 1 second

Guidelines for simultaneous connection of Bluetooth and 2.4G Dual-mode
Step: Pair 2.4G first, then Bluetooth

Kindly Note

EN

If the battery level drops below 10%, there will be a low battery warning.
When powering on, the headset provides a battery status voice prompt: Battery High / Medium / Low.
When fully charged, the indicator light turns green.
In Bluetooth mode, the battery level icon will be shown on the connected phone.

DE

Wenn der Akkustand unter 10 % fällt, erscheint eine Akkustandswarnung.
Beim Einschalten gibt es eine Sprachansage zum Akkustand: Battery High / Medium / Low
Im vollaufgeladenen Zustand leuchtet die Anzeige grün.
Im Bluetooth-Modus wird das Akkusymbol auf dem verbundenen Smartphone angezeigt.

JP

バッテリー残量が10%以下になると、バッテリー残量低下の警告が表示されます。
電源を入れると、バッテリー残量の音声案内があります：Battery High / Medium / Low
フル充電状態では、インジケーターランプが緑色に点灯します。
Bluetoothモードでスマートフォンに接続すると、スマホ画面にバッテリーレベルのアイコンが表示されます。

Changing Ear Cap Cushions

For extended wearing comfort, we recommend using the Fabric Ear Cushions, which come pre-installed on your headset.

If you prefer a stronger Active Noise Cancellation (ANC) performance and enhanced noise isolation, switch to the Leather Ear Cushions supplied in the accessory kit.

How to Replace the Ear Cushions:
1. Hold the ear cushion firmly and gently pull it outward to detach it from the headset frame.
2. Align the replacement cushion with the edges of the ear cup.
3. Press around the edges until it securely fits into place.

The cushions are designed with a simple press-fit mechanism, making it easy to swap cushions anytime based on your comfort and listening preference.

Dual-Mode (2.4G Dongle & BT) Pairing Instructions

1. First-time Use
After powering on, the headset enters pairing mode and will connect to either the 2.4G Dongle or BT (only one mode at a time). To pair the second mode, quickly tap the "MFB button 5 times in a row" until the headset prompts "pairing".
At this point, insert the dongle into the target device to wait for pairing.
or enable BT on your phone, search for the headset's pairing name and select it to complete Bluetooth pairing. Once both modes are successfully paired, the audio source will switch automatically, with the headset playing the most recently activated audio.

2. Subsequent Dual-Mode Connection
To enable dual-mode connectivity after each power-off, follow the above pairing process, with one key difference:
•If the 2.4G Dongle is connected first, the headset will automatically reconnect to the paired phone's BT when the phone's BT is turned on.

• If BT is connected first, you need to quickly tap the "MFB button 5 times" to put the headset back into pairing mode, then insert the dongle into the corresponding device (e.g., computer or phone) for the headset to automatically search and pair with the dongle.

Note
Once dual-mode pairing is completed, audio source switching cannot be done via the headset itself and must be operated on the connected devices—the headset will automatically play the most recently played audio. In addition, the call mode has the highest priority.

EN Hybrid ANC Wireless Headphones User Manual

LED Indicator

- Pairing status: red and blue lights flash alternately
- Successful pairing: blue light flashes for 1 second
- Charging status: red light is always on
- Charging complete: green light always on

BT pairing

1. Please make sure that the distance between the BT earphones and the cell phone (or other connected devices) is within 1 meter, the closer the distance, the easier the pairing of the earphones.
2. Without connecting any external devices, press and hold the function button until the red and blue lights flash rapidly, then the earphones enters the pairing mode.
3. Turn on the BT function of your cell phone (or other BT devices) and search or scan, Then select "LIVEY 950BT" from the list of available BT devices, When the blue light blinks for 1s, it means the pairing is successful.
4. BT automatic connection
After pairing, the earphones will automatically connect to the last connected device when you use it again. If the BT connection is successful, the headset will automatically reconnect if the effective distance is exceeded and the earphones returns to the effective distance within 5 minutes.

2.4G connection

After the USB receiver is plugged into the PC device, you need to select the audio output/input type on the PC device: LIVEY 950BT, if the USB receiver is plugged into another handheld device, it is the receiver output/input by default.

Active Noise Cancellation

1. In the power-on state, click the ANC button to enter the pass-through mode, the Click again to enter ANC ON mode, and press ANC OFF again
2. Clicking the ANC button after powering on will cycle between pass-through/ANC ON/ ANC OFF modes
3. In the off state, long press the ANC key to turn on ANC, then press it again to turn off ANC, and then press it again to enter "pass through" mode。 (pass through: a function that allows users to hail ambient sounds while wearing headphones.)

Charging the headset

1. Connect the charger to the Type-C charging cable that comes with the earphones;
2. During charging, the indicator light will turn red;
3. When the earphones is fully charged, the red indicator light will turn off and the Green indicator light will be always on, unplug the charger from the power outlet;
4. Only chargers that have been approved by the Company may be used, non-approved or non-Company chargers may result in damage to the earphones or cause an explosion in extreme environments, and may also void any warranty on the product.
5. Repeated charging and discharging of the earphones will result in a decrease in battery performance over time, which is normal for all rechargeable batteries.

Safety Rules

1. This product is not a toy, children should use the headphones under adult supervision;
2. Do not expose the device to excessive high or low temperatures (below 0°C and above 45°C);
3. Avoid placing the device near the eyes of children or animals;
4. Do not wear the device for long periods of time when using it at high volume. Avoid damage to your hearing;
5. For travel safety, please pay attention to traffic safety when using the headset while driving or walking;
6. In order to ensure your personal safety, please do not wear or place the headset too close to the pacemaker (less than 10CM);
7. Do not use the BT device in thunderstorms, as thunderstorms can cause the device to work improperly and increase the risk of electric shock.

DE Kabellose Hybrid-ANC-Kopfhörer Bedienungsanleitung

LED-Anzeige

- Pairing-Status: rote und blaue Lichter blinken abwechselnd
- Erfolgreiches Pairing: blaues Licht blinkt für 1 Sekunde
- Ladestatus: rotes Licht leuchtet immer
- Ladevorgang abgeschlossen: grünes Licht leuchtet immer

BT-Paarung

1. Bitte stellen Sie sicher, dass der Abstand zwischen dem BT-Kopfhörer und dem Mobiltelefon (oder oder anderen angeschlossenen Geräten) nicht mehr als 1 Meter beträgt, je geringer der Abstand, desto einfacher ist die das Pairing des Kopfhörer.
2. Halten Sie, ohne ein externes Gerät anzuschließen, die Funktionstaste gedrückt, bis die roten und blauen roten und blauen Lichter schnell blinken, dann wechselt das Kopfhörer in den Pairing-Status.
3. Schalten Sie die BT-Funktion Ihres Handys (oder anderer BT-Geräte) ein und suchen oder scannen Sie, Wählen Sie dann „LIVEY 950BT" aus der Liste der verfügbaren BT-Geräte aus. Wenn das blaue Licht 1s lang blinkt 1s lang blinkt, bedeutet dies, dass das Pairing erfolgreich war.
4. Automatische BT-Verbindung:
Nach dem Pairing verbindet sich das Kopfhörer automatisch mit dem zuletzt verbundenen Gerät wenn Sie es erneut verwenden. Wenn die BT-Verbindung erfolgreich ist, wird das Kopfhörer Wenn die BT-Verbindung erfolgreich hergestellt wurde, stellt das Kopfhörer die Verbindung automatisch wieder her, wenn die effektive Entfernung überschritten wird und das Kopfhörer innerhalb von 5 Minuten zur effektiven Entfernung zurückkehrt.

2-4G connection

Nachdem der USB-Empfänger an das PC-Gerät angeschlossen wurde, müssen Sie den Audio Ausgangs-/Eingangstyp auf dem PC-Gerät auswählen: LIVEY 950BT. Wenn der USB-Empfänger an ein anderes Handgerät angeschlossen ist Handheld-Gerät angeschlossen ist, ist das standardmäßig der Empfängerausgang/-eingang.

Aktive Geräuschunterdrückung

1. Klicken Sie im eingeschalteten Zustand auf die ANC-Taste, um in den Pass-Through-Modus zu wechseln, Klicken Sie erneut auf um den Modus ANC ON zu aktivieren, und drücken Sie erneut auf ANC OFF.
2. Wenn Sie nach dem Einschalten auf die ANC-Taste klicken, wechseln Sie zwischen den Modi Pass-Through/ANC ON/ANC AUSMODI
3. Drücken Sie im ausgeschalteten Zustand lange auf die ANC-Taste, um ANC einzuschalten, drücken Sie sie dann erneut, um den „Pass through"-Modus zu aktivieren, und drücken Sie sie dann erneut, um in den „Zurückgemeldet" zu gelangen. (Pass-Through: eine Funktion, mit der Benutzer Umgebungsgeräusche wahrnehmen können, während sie Kopfhörer tragen.)

Aufladen des Headsets

1. Schließen Sie das Ladegerät an das Typ-C-Ladekabel an, das mit dem Kopfhörer geliefert wird.
2. Während des Ladevorgangs leuchtet die Anzeigelampe rot;
3. Wenn der Kopfhörer vollständig aufgeladen ist, erlischt die rote Anzeige und die grüne Die blaue Anzeige leuchtet immer, Ziehen Sie das Ladegerät aus der Steckdose.
4. Es dürfen nur von der Firma zugelassene Ladegeräte verwendet werden, nicht zugelassene Nicht zugelassene oder unternehmensfremde Ladegeräte können das Produkt beschädigen oder unter extremen Umgebungen eine Explosion verursachen und können außerdem zum Erlöschen der Garantie für das Produkt führen.
5. Wiederholtes Aufladen und Entladen des Kopfhörer führt mit der Zeit zu einer Abnahme der Akkuleistung, Dies ist bei allen wiederaufladbaren Batterien normal.

Sicherheitsregeln

1. Dieses Produkt ist kein Spielzeug, Kinder sollten die Kopfhörer unter Aufsicht von Erwachsenen benutzen;
2. Setzen Sie das Gerät nicht zu hohen oder niedrigen Temperaturen aus (unter 0°C und über 45°C);
3. Vermeiden Sie es, das Gerät in der Nähe der Augen von Kindern oder Tieren zu bringen;
4. Tragen Sie das Gerät nicht über einen längeren Zeitraum, wenn Sie es mit hoher Lautstärke verwenden. Vermeiden Sie Schäden an Ihrem Gehör;
5. Achten Sie aus Sicherheitsgründen auf die Verkehrssicherheit, wenn Sie das Headset während des während des Fahrens oder Gehens;
6. Um Ihre persönliche Sicherheit zu gewährleisten, tragen oder platzieren Sie das Headset bitte nicht zu nahe in der Nähe des Herzschrittmachers (weniger als 10 cm);
7. Verwenden Sie das BT-Gerät nicht bei Gewitter, da Gewitter die Funktion des Gerätes kann das Gerät nicht ordnungsgemäß funktionieren und das Risiko eines Stromschlags erhöhen.

JP ハイブリッド ANC ワイヤレス ヘッドフォン ユーザーマニュアル

LEDインジケーター

- ペアリング状態：赤と青のライトが交互に点滅します。
- ペアリング成功：青いライトが1秒間点滅します。
- 充電状態：赤色ライトが常時点灯
- 充電完了：緑ライトが常時点灯

BTペアリング

1. BTヘッドセットと携帯電話（または他の接続デバイス）の距離が 1m 以内であることを確認してください。距離が近いほど、ヘッドセットのペアリングが簡単になります。距離が近いほど、ヘッドセットのペアリングが簡単になります。
2. 外部デバイスを接続せずに、機能ボタンを赤と青のライトが速く点滅するまで押し続けます。赤と青の点滅が速く点滅するまで押し続けます。ヘッドセットはペアリングモードに入ります。
3. 携帯電話（またはその他の BT デバイス）の BT 機能をオンにし、検索またはスキャンします。次に、使用可能な BT デバイスリストから「LIVEY 950BT」を選択します。青いライトが1秒間点滅したら、ペアリングが完了したことを意味します。
1 秒間点滅したら、ペアリングが 成功したことを意味します。
4. BT 自動接続:
ペアリング後、ヘッドセットを再度使用する際、ヘッドセットは自動的に最後に接続したデバイスに接続します。正確性に接続します。BT 接続が成功すると、ヘッドセットはこのようになります。有効距離を超えると、ヘッドセットは自動的に再接続します。5 分以内に有効距離に戻ります。

2.4G接続

USBレシーバーをPCデバイスに接続した後、PCデバイスでオーディオ出力/入力タイプを選択する必要があります。を選択する必要があります：LIVEY 950BT。
USBレシーバーが別の を選択する必要があります。

アクティブノイズキャンセリング

1. 電源オン状態で、ANCボタンをクリックするとパススルーモードになり、再度クリックするとANCオンモードになります。をもう一度クリックしてANC OFFを押します。
2. 電源オン後にANCボタンをクリックすると、パススルー(ANC ON/ANC OFFモードがひと巡りします。ANC OFFまで。
3. オフの状態でANCキーを長押しし、ANCをオンにします。パススルーモードになります。
（パススルー：ヘッドホンを装着した状態で周囲の音を感じられる機能）。

ヘッドセットの充電

1. 充電器をヘッドセットに付属のType-C 充電ケーブルに接続します;
2. 充電中、インジケーターライトが赤く点灯します;
3. イヤセンが完全に充電されると、赤いインジケーターランプが消え、緑色のインジケーターランプが常に点灯します。充電器をコンセントから抜いてください;
4. 当社が承認した充電器のみを使用できます。機械的環境では、ヘッドセットの損傷または爆発を引き起こす可能性があります。また、製品の保証が無効になる場合があります;
5. ヘッドセットの充電と放電を繰り返すと、時間の経過とともにバッテリーの性能が低下します。ヘッドセットの充電と放電を繰り返すと、時間の経過とともにバッテリーの性能が低下します。

安全ルール

1. 本製品はおもちゃではありませんので、お子様は大人の監督のもとでヘッドホンを使用してください;
2. デバイスを過度の高温または低温にさらさないでください。45℃);
3. 子供や動物の目の近くにデバイスを置かないでください;
4. 大音量で使用する際は、長時間装着しないでください。以下のことを避けてください。聴覚への損傷を避けてください;
5. 移動の安全のため、運転中または歩行中にヘッドセットを使用する際は、交通安全に注意してください。運転中または歩行中にヘッドセットを使用する場合は、交通安全に注意してください;
6. 自分安全を確保するため、ヘッドセットをペースメーカーに近づけすぎないようにしてください。ペースメーカーに近づけすぎないようにしてください（10CM 以下）;
7. 雷雨はデバイスを不適切に動作させ、感電の危険性を高めます。雷雨はデバイスが正常に動作せず、感電の危険性が高まります。

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Any changes or modifications not expressly approved by the party responsible for compliancecould void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
– Reorient or relocate the receiving antenna.
– Increase the separation between the equipment and receiver.
– Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
– Consult the dealer or an experienced radio/TV technician for help.
The device has been evaluated to meet general RF exposure statement.
The device can be used in portable exposure condition without restriction.